

Cable Door Switch for EL LED Enclosure Lights

Ready to use cables for infeed power, through wiring and door switches. The cables are available in different colors.

FEATURES

Description: Pre-fabricated cables for LED enclosure lights. Using these cables will save time and ease mounting of the lights.

Connection: Infeed, with through wiring 3-pole cables (24V is with 2-pole cable).

Dimensions: Different lengths: See article list for more info.



Material: Copper
Finish: Smooth

SPECIFICATIONS

Catalog Number	E-Number	Product Family	Color	Length	Cable Type	Connection Type
ELC3001DU	3303039	IEC General Accessories	Black	3000m m	Cable for Door Switch	TPS-Cable for Doorswitch, UL Version
ELC1005PB	3303026	IEC General Accessories	Black	1000m m	Connection Cable	Infeed, 3 Pole, 100-240 V AC
ELC1005PO	3303029	IEC General Accessories	Orange	1000m m	Connection Cable	Infeed, 3 Pole, 100-240 V AC
ELC1005TB	3303030	IEC General Accessories	Black	1000m m	Through Wiring	Trough-Wiring, 3 Pole, 100-240 V AC
ELC1005TG24V	3303032	IEC General Accessories	Gray	1000m m	Through Wiring	Trough-Wiring, 2-Pole, 24 V (DC)
ELC1005TO	3303033	IEC General Accessories	Orange	1000m m	Through Wiring	Trough-Wiring, 3 Pole, 100-240 V AC
ELC3001DE	3303038	IEC General Accessories	Black	3000m m	Cable for Door Switch	TPS-Cable for Doorswitch, ENEC Version
ELC3005PB	3303040	IEC General Accessories	Black	3000m m	Connection Cable	Infeed, 3 Pole, 100-240 V AC

Catalog Number	E-Number	Product Family	Color	Length	Cable Type	Connection Type
ELC3005PG24V	3303042	IEC General Accessories	Gray	3000m m	Connection Cable	Infeed, 2-Pole, 24 V (DC)
ELC3005PO	3303043	IEC General Accessories	Orange	3000m m	Connection Cable	Infeed, 3 Pole, 100-240 V AC

ADDITIONAL PRODUCT DETAILS

UL Version – ready-to-use TPS cable for door switch (UL-listed).

WARNING

nVent products shall be installed and used only as indicated in nVent's product instruction sheets and training materials. Instruction sheets are available at www.nvent.com and from your nVent customer service representative. Improper installation, misuse, misapplication or other failure to completely follow nVent's instructions and warnings may cause product malfunction, property damage, serious bodily injury and death and/or void your warranty.

