

Cable Door Switch for EL LED Enclosure Lights



Ready to use cables for infeed power, through wiring and door switches. The cables are available in different colors.

FEATURES

Description: Pre-fabricated cables for LED enclosure lights. Using these cables will save time and ease mounting of the lights.

Connection: Infeed, with through wiring 3-pole cables (24V is with 2-pole cable).

Dimensions: Different lengths: See article list for more info.

Material: Copper
Finish: Smooth

SPECIFICATIONS

Catalog Number	E-Number	Product Family	Color	Length	Cable Type	Connection Type
ELC3001DU	2504783	IEC General Accessories	Black	3000m m	Cable for Door Switch	TPS-Cable for Doorswitch, UL Version
ELC1005PB	2504581	IEC General Accessories	Black	1000m m	Connection Cable	Infeed, 3 Pole, 100-240 V AC
ELC1005PO	2504578	IEC General Accessories	Orange	1000m m	Connection Cable	Infeed, 3 Pole, 100-240 V AC
ELC1005TB	2505532	IEC General Accessories	Black	1000m m	Through Wiring	Trough-Wiring, 3 Pole, 100-240 V AC
ELC1005TG24V	2505533	IEC General Accessories	Gray	1000m m	Through Wiring	Trough-Wiring, 2-Pole, 24 V (DC)
ELC1005TO	2505534	IEC General Accessories	Orange	1000m m	Through Wiring	Trough-Wiring, 3 Pole, 100-240 V AC
ELC3001DE	2504782	IEC General Accessories	Black	3000m m	Cable for Door Switch	TPS-Cable for Doorswitch, ENEC Version
ELC3005PB	2504585	IEC General Accessories	Black	3000m m	Connection Cable	Infeed, 3 Pole, 100-240 V AC

Catalog Number	E-Number	Product Family	Color	Length	Cable Type	Connection Type
ELC3005PG24V	2504574	IEC General Accessories	Gray	3000m m	Connection Cable	Infeed, 2-Pole, 24 V (DC)
ELC3005PO	2504580	IEC General Accessories	Orange	3000m m	Connection Cable	Infeed, 3 Pole, 100-240 V AC

ADDITIONAL PRODUCT DETAILS

UL Version – ready-to-use TPS cable for door switch (UL-listed).

WARNING

nVent products shall be installed and used only as indicated in nVent's product instruction sheets and training materials. Instruction sheets are available at www.nvent.com and from your nVent customer service representative. Improper installation, misuse, misapplication or other failure to completely follow nVent's instructions and warnings may cause product malfunction, property damage, serious bodily injury and death and/or void your warranty.

